NSN 6105-01-310-7926

Alternating Current Motor - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/6105-01-310-7926

Overall Height:
8.3545 inches
Overall Length:
12.290 inches
Keyway Width:
0.188 inches single end
Shaft Diameter:
0.6245 inches single end and 0.6250 inches single end
Duty Cycle:
Continuous
Inclosure Feature:
Totally enclosed
Mounting Method:
Fixed base
Mounting Facility Type And Quantity:
4 unthreaded hole
Cooling Method:
Fan cooled
Key Height Above Shaft:
0.188 inches single end
Frame Size Designation:
J56c
Power Rating:
0.500 horsepower output
Length Of Shaft From Housing:
1.880 inches single end
Center To Center Distance Between Mounting Facilities Parallel To Length:
3.000 inches
Tempurature Rating:
40.0 ambient degrees celsius
Rotor Speed Rating In Rpm:
Rotor Speed Rating In Rpm: 3450.0 single full load
3450.0 single full load
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width:
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width: 4.880 inches
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width: 4.880 inches Current Rating In Amps:
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width: 4.880 inches Current Rating In Amps: 3.700 first multiple input or 7.400 second multiple input
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width: 4.880 inches Current Rating In Amps: 3.700 first multiple input or 7.400 second multiple input Connection Type And Voltage Rating In Volts:
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width: 4.880 inches Current Rating In Amps: 3.700 first multiple input or 7.400 second multiple input Connection Type And Voltage Rating In Volts: 115.0 line to neutral low input or 230.0 line to neutral high input
3450.0 single full load Center To Center Distance Between Mounting Facilities Parallel To Width: 4.880 inches Current Rating In Amps: 3.700 first multiple input or 7.400 second multiple input Connection Type And Voltage Rating In Volts: 115.0 line to neutral low input or 230.0 line to neutral high input Shaft End Characteristic:

NSN 6105-01-310-7926

Alternating Current Motor - Page 2 of 2



Frequency In Hertz:	Freq	uency	ln	Hertz:
---------------------	------	-------	----	--------

60.0 input

Fsc Application Data:

Electricalmotors

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

A271a0