Motor Starter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/6110-00-212-9130

# Speed Adjustments:

Single speed

## **Overall Length:**

17.500 inches

## **Overall Height:**

21.000 inches

## **Overall Width:**

9.000 inches

#### Ac Voltage Rating:

440.0 volts

#### **Frequency Rating:**

60.0 hertz

#### **Actuation Method:**

Magnetic

#### Performance Type:

Automatic

## **Fuse Accommodation Quantity:**

2

#### Duty Cycle:

Continuous

# Mounting Configuration:

Six 17/32 in. Diameter mtg holes arranged in 2 row of 3 holes ea with 18 in. Between rows and holes 6-3/4 in. C to c

## **Operating Voltage Characteristic:**

Full

#### Horsepower Rating:

25.000

#### **Actuator Voltage:**

440.0 ac

## **Fuse Current Rating In Amps:**

10.0

# Load Protection Type:

Overload and undervoltage

# Ambient Temp:

50.0 degrees celsius

# Inclosure Feature:

Dripproof

# National Electrical Manufacturers Association Standards Design:

Not designed per nema std

# **Switch Functional Positions:**

Start and stop and reset and manual and automatic

# **Control Type:**

Local

# NSN 6110-00-212-9130

Motor Starter - Page 2 of 2

# Features Provided:

Circuit protection fuse

Phase:

Three

Frequency In Hertz:

60.0

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

A541c0

