NSN 6110-01-166-3856

Motor Starter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/6110-01-166-3856

Speed Adjustments:
0 to full speed
Hazardous Locations/environmental Protection:
Industrial use-nema type 12
Overall Length:
9.875 inches
Overall Height:
5.000 inches
Overall Width:
4.750 inches
Ac Voltage Rating:
208.0 volts and 380.0 volts
Frequency Rating:
60.0 hertz
Actuation Method:
Manual
Performance Type:
Manual
Size Designator:
0
Duty Cycle:
Continuous
Mounting Configuration:
Four holes for nom no. 10 screw fastener; rectangular pattern; on 3 in. By 9 in. Centers
Operating Voltage Characteristic:
Full
Horsepower Rating:
3.000 and 5.000
Load Protection Type:
Overload
Ambient Temp:
50.0 degrees celsius
Inclosure Feature:
Dust tight
National Electrical Manufacturers Association Standards Design:
Designed per nema std
Switch Functional Positions:
Start and stop
Control Type:
Local
Phase:
Three

NSN 6110-01-166-3856

Motor Starter - Page 2 of 2



Rated 3 hp at 208/230v; 5 hp at 380/575v

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

A541c0