NSN 6110-01-302-5418

Motor Starter - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/6110-01-302-5418

Speed Adjustments:
Single speed
Hazardous Locations/environmental Protection:
Dripproof
Ac Voltage Rating:
460.0 volts
Frequency Rating:
60.0 hertz
Actuation Method:
Magnetic
End Application:
Vent fans controller
Fuse Accommodation Quantity:
2
Size Designator:
2
Mounting Configuration:
Wall mount
Operating Voltage Characteristic:
Full
Horsepower Rating:
15.000
Fuse Current Rating In Amps:
2.5
Load Protection Type:
Undervoltage
Ambient Temp:
50.0 degrees celsius
Inclosure Feature:
Dripproof
National Electrical Manufacturers Association Standards Design:
Designed per nema std
Amp Size Rating:
20.0
Switch Functional Positions:
Stop and emergency stop and remote and start and run and reset
Control Type:
Remote
Features Provided:
Circuit protection fuse
Phase:
Three

NSN 6110-01-302-5418

Motor Starter - Page 2 of 2



	Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

A541c0