NSN 6115-00-843-8501

Prime Mover Cooling Medium:

Gasoline Engine Generator Set - Page 1 of 2



View Online at https://aerobasegroup.com/nsn/6115-00-843-8501

Air
Mounting Type:
Wheel
Overall Length:
104.000 inches
Overall Height:
58.000 inches
Overall Width:
54.000 inches
Current Type:
Ac and dc
Dc Voltage Rating:
28.0 volts
Frequency Rating:
400.0 hertz
Accessory Component Quantity:
1 and 1
Inclosure Type:
Fully enclosed
Accessory Controlling Agency:
Ana; ana
Accessory Identifying Number:
An2551e30 part no. And an3430-5 part no.
Winterization Feature:
Included
Ac Wattage Rating:
45.0 kilowatts
Dc Wattage Rating:
15.0 kilowatts
Line To Line Voltage In Volts:
200.0
Line To Neutral Voltage In Volts:
115.0
Power Factor In Percent:
0.8
Excitor Type:
Self-excited
Prime Mover Starting Method:
Electric motor
Automatic Starting Feature:
Not provided

NSN 6115-00-843-8501

Gasoline Engine Generator Set - Page 2 of 2



Prime Mover Manufacturer Name:
Continental motors corp.
Prime Mover Identifying Number:
Model be150-6
Housing Type:
Inclosed
Accessory Component Name:
Cable, cable
Ambient Tempurature In Deg Celsius:
-54.0 and 55.0
Tempurature Rise Rating In Deg Celsius For Continuous Operation:
Not rated
Radio Interference Suppression:
Included
Phase:
Three
Reference Number Differentiating Characteristics:
Acdc, afhs, akvy, azcg, akvz
Shelf Life:
N/a
Unit Of Measure:
Demilitarization:
No
Fiig:
T322-a