Alternating Current Generator - Page 1 of 1



View Online at https://aerobasegroup.com/nsn/6115-01-371-2683

# Keyway Width:

0.250 inches single end

### Keyway Depth:

0.250 inches single end

## Shaft Diameter:

1.120 inches single end

## Keyway Length:

3.120 inches single end

#### **End Application:**

Ws133

### **Mounting Method:**

Fixed base

## Mounting Facility Type And Quantity:

4 unthreaded hole

#### **Power Rating:**

9.6 kilowatts output

## Shaft Center To Mounting Surface Distance:

4.620 inches single end

## Center To Center Distance Between Mounting Facilities Parallel To Length:

12.000 inches

## Center To Center Distance Between Mounting Facilities Parallel To Width:

3.750 inches

### **Current Rating In Amps:**

28.900 high output

## **Connection Type And Voltage Rating In Volts:**

240.0 line to line single output

#### Shaft End Characteristic:

A9 single style single end

## Phase:

Three output

#### **Special Features:**

Model mb-120-3, 12kva, 9.6kw, .8 pf 240 volts. 3 phase, 60 hz, 28.9 amps. Special winding (g-1 option). 24 hp required at 3600 rpm. Approx wt.127 lbs. Generator to be supplied without control box. Generator to be supplied with end cover. Pc board to be mounted inside this generator.

#### **Frequency In Hertz:**

60.0 output

### Shelf Life:

N/a

# Unit Of Measure:

--

## Demilitarization:

No

Fiig:

A271a0