

View Online at <https://aerobasegroup.com/nsn/6115-01-494-8790>

Prime Mover Cooling Medium:

Air

Current Type:

Ac and dc

Direct Current Rating In Amps:

8.3

Dc Voltage Rating:

12.0 volts

End Application:

5000e portable generator set

Inclosure Type:

Partially enclosed

Identifying Number:

Rgd5000e model no.

Manufacturer Name:

Norwall power systems

Ac Wattage Rating:

4500.0 watts

Dc Wattage Rating:

100.0 watts

Line To Line Voltage In Volts:

120.0 and 240.0

Excitor Type:

Self-excited

Prime Mover Starting Method:

Exciter

Phase:

Single

Special Features:

May also be powered by jp-5 jet fuel or diesel light oil

Supplementary Features:

Voltage regulator: condensor type; frequency: 60 hz; fuel tank capacity: 4.23 gallons (16.0l); 8.0 hours continuous hours; power factor: 1.0; engine model: dy41d

Shelf Life:

N/a

Unit Of Measure:

--

Demilitarization:

No

Fiig:

T322-a