

View Online at <https://aerobasegroup.com/nsn/6115-01-494-8790>

**Prime Mover Cooling Medium:**

Air

**Current Type:**

Ac and dc

**Direct Current Rating In Amps:**

8.3

**Dc Voltage Rating:**

12.0 volts

**End Application:**

5000e portable generator set

**Inclosure Type:**

Partially enclosed

**Identifying Number:**

Rgd5000e model no.

**Manufacturer Name:**

Norwall power systems

**Ac Wattage Rating:**

4500.0 watts

**Dc Wattage Rating:**

100.0 watts

**Line To Line Voltage In Volts:**

120.0 and 240.0

**Excitor Type:**

Self-excited

**Prime Mover Starting Method:**

Exciter

**Phase:**

Single

**Special Features:**

May also be powered by jp-5 jet fuel or diesel light oil

**Supplementary Features:**

Voltage regulator: condensor type; frequency: 60 hz; fuel tank capacity: 4.23 gallons (16.0l); 8.0 hours continuous hours; power factor: 1.0; engine model: dy41d

**Shelf Life:**

N/a

**Unit Of Measure:**

--

**Demilitarization:**

No

**Fiig:**

T322-a