## NSN 6625-01-033-0735

Ammeter - Page 1 of 2

External



View Online at https://aerobasegroup.com/nsn/6625-01-033-0735

Circuit Current For Which Designed:
Dc
Overall Length:
2.315 inches
Mounting Hole Diameter:
Between 0.143 inches and 0.157 inches
Scale Division Quantity:
75 single indicator single range
Overall Diameter:
3.500 inches
Environmental Protection:
Cold resistant and heat resistant and shock resistant and submersible and vibration resistant and watertight
Mounting Bolt Circle Diameter:
3.160 inches
Furnished Items And Quantity:
Nut 5; washer 5
Indicator Type:
Dial w/pointer
Installation Design:
Panel
Mounting Arrangement Style:
Three hole/stud bolt circle
Sensitivity Rating:
50.0 millivolts
Dial Scale Marking Color:
Black single indicator single range
Accuracy In Percent:
-2.0/+2.0 at full scale single indicator single range
Unable To Decode:
Unable to decode or unable to decode
Meter Depth Behind Mounting Flange:
1.190 inches
Meter Body Diameter Behind Mounting Flange:
2.800 inches
Movement Type:
Moving coil, permanent magnet
Background Color:
White single indicator single range
Pointer Color:
Black single indicator single range
Power Source:

## NSN 6625-01-033-0735

Ammeter - Page 2 of 2



Mounting Facility Type And Quantity:
3 screw and 3 unthreaded hole
Scale Graduation Type:
Linear single indicator single range
Measurement Range:
+0.0/+15.0 amperes, dc single indicator single range
Features Provided:
Luminous scale marking and magnetic shield and zero adjuster
Movement Suspension Method:
Jewel pivot base
Circuit Attachment Method And Quantity:
2 solder lug and 2 threaded stud
Special Features:
Ruggedized
Special Markings:
P sign and sealed do not open on face of meter
Material:
Stainless steel
Nuclear Hardness Critical Feature:
Nonhardened
Surface Treatment:
Enamel semigloss
Special Test Features:
Conforms to mil-m-10304/12 type mr36w015dcaar
Style Designator:
Round flush mtg
Fsc Application Data:
Test set, elect. Equip.
Shelf Life:
N/a
Unit Of Measure:
Demilitarization:
No
Fiig:
A310a0